

How can I configure My Modem (Our Modems)

- ***Technicolor v1-Thomson :***

- Connect to the Wi-Fi network of your modem.
- Open any browser, and enter the gateway address (the default one is 192.168.1.254)
- Click on Technicolor or Thomson Gateway → Setup my Thomson-Technicolor gateway

Thomson TG585 v8

THOMSON

Logged in as: Administrator

Home > Thomson Gateway

Thomson Gateway

- **Information**
 - Product Name: TG585 v8
 - Serial Number: CP1111SFFV3
 - Software Release: 8.2.7.A
- **Configuration**
 - Service Name: Routed PPP (modified by user)
 - Date & Time: Fri, 31-Dec-1999 19:08:51-05:00

Pick a task...

- Setup my Thomson Gateway 2
- Restart my Thomson Gateway
- Reset my Thomson Gateway
- View event logs
- Check connectivity to the Internet

- Click Next
- Select a service : routed PPP

Select the service of your DSL account. Click Next to continue.


Select a service:


IP Routed
Routed PPP
Bridge

Description of selected service:

DESCRIPTION	Routed Connection.
REGION	North America
PROVIDER	Generic

- VPI/VCI: 0/35 (Ogero), 8/35 (GDS), connections type: routed PPP over Ethernet


Routed Internet Connection
Specify the details of the Internet connection. All information should be provided by your ISP. 

VPI/VCI 
Choose a VPI/VCI from the list

Connection Type PPP over ATM (PPPoA)
 PPP over Ethernet (PPPoE)

- Internet account setting: username X123456@idm.net.lb / password : XXXXXX

highspeed.tips/emulators/585v8/cgi/wizard/r3.htm

Internet Account Settings
Specify the details of your Internet Account. All information should be provided by your ISP. 

User Name
Enter your Internet connection user name.

Password
Enter your Internet connection password.

Confirm Password
Re-enter your password.

- Access control: skip or any credentials you want
- Start
- Finish.